

DUAL-RADIO WIRELESS DMX RECEIVER & MERGER

DUAL RX

Two independent TimoTwo receivers, one DMX output, automatic best-signal merge – with 24+ hours of battery.



The Dual RX puts two complete LumenRadio TimoTwo receivers in one box, feeding a single DMX output. Link each radio to a different transmitter and the merge function selects the active source automatically – based on wireless connectivity, signal strength and a valid DMX stream – so a failing link never interrupts the output. For manual control, a slide switch hard-selects RX A or RX B. The built-in rechargeable battery runs for over 24 hours, making it ideal for set-mounted and remote positions.

- 2× TimoTwo
- Auto merge
- 24+ h battery
- 1 DMX out

FEATURES

- Two independent LumenRadio TimoTwo receivers in one enclosure
- Each radio links to its own transmitter – true dual-link redundancy
- Automatic merge picks the receiver with the best link and a valid DMX stream
- Manual override via front-panel slide switch (RX A / RX B)
- Built-in rechargeable battery – 24+ hours of runtime
- Single DMX output on 5-pin XLR

SPECIFICATIONS

DMX CAPACITY	1 universe out (512 channels)
RADIOS	2 × LumenRadio TimoTwo (independent links)
MERGE	Automatic (link quality + valid DMX) or manual slide switch
BATTERY	Built-in rechargeable, 24+ h runtime
INPUT VOLTAGE	5-24 V DC via barrel connector
ANTENNA CONNECTORS	2 × RP-TNC
DIMENSIONS	59 × 42 × 130 mm (2.3 × 1.7 × 5.1 in) excl. antennas

IN THE BOX

- SKT Dual RX wireless DMX receiver
- 2 × RP-TNC antennas
- USB-to-barrel pigtail