

4-UNIVERSE CRMX TRANSMITTER WITH SACN / ART-NET NODE

SKT4 TRANSMITTER

Four independent CRMX universes plus a built-in network node – feed it sACN or Art-Net straight from the console.



The SKT4 is four wireless transmitters and a network node in one box. Each of its four CRMX universes pairs independently to compatible receivers, and the built-in sACN/E1.31 and Art-Net node means the source can be a lighting network instead of four DMX lines – one RJ45 from the switch and you're on air. Configuration runs over the network using DMXKing software. Power comes in on Neutrik PowerCon or straight over PoE.

4 universes

sACN / Art-Net

PoE 802.3af

PowerCon

FEATURES

- Four independent CRMX universes – 512 channels each
- Each universe pairs independently to any CRMX-compatible receiver
- Built-in sACN/E1.31 and Art-Net node on RJ45
- Network configuration via DMXKing software
- Powered by 90-240 V AC on Neutrik PowerCon or PoE (IEEE 802.3af)
- Four external antennas on RP-TNC

SPECIFICATIONS

DMX CAPACITY	4 universes (512 channels each)
RADIO	LumenRadio CRMX (TimoTwo)
NETWORK PROTOCOLS	sACN / E1.31, Art-Net
CONFIGURATION	RJ45, DMXKing software
POWER	90-240 V AC 50/60 Hz (Neutrik PowerCon) or PoE IEEE 802.3af
DIMENSIONS	190 × 120 × 55 mm (7.4 × 4.7 × 2.2 in)

IN THE BOX

- ▶ SKT4 TX transmitter with integrated network node
- ▶ 4 × antennas
- ▶ PowerCon feeder cord